

## MEGAVOX 2

Portable Public Address System



## Perfect for...

- Indoor & Outdoor Events
- Schools & Universities
- Military Training
- Sporting Events
- Band & Guard Practice
- Announcements
- Firing Ranges
- Parks and Recreation
- Auctions
- First Responders
- Emergency Preparedness
- Public Gatherings
- and more!




Anchor Audio | 800.262.4671 | sales@anchoraudio.com | anchoraudio.com



## TECH SPECS

- 119 dB of clear sound
- 20W AC/DC mode

- Built-in Class 1 Bluetooth
  Signal alert button
  Built-in rechargeable batteries operate 6 8 hours on a single charge



(MEGA2-XU4 Back Panel)

MegaVox 2 Models		
MEGA2	MegaVox with built-in Bluetooth	
MEGA2-U2	MegaVox with built-in Bluetooth & dual wireless mic receiver	
MEGA2-U4	MegaVox with built-in Bluetooth & two dual wireless mic receivers	
MEGA2-X	MegaVox with built-in Bluetooth & AIR transmitter	
MEGA2-XU2	MegaVox with built-in Bluetooth, AIR transmitter & dual wireless mic receiver	
MEGA2-XU4	MegaVox with built-in Bluetooth, AIR transmitter & two dual wireless mic receivers	
MEGA2-AIR	MegaVox AIR wireless companion speaker	
MEGA2-COMP	MegaVox unpowered wired companion speaker	
Microphones		
WH-LINK	Wireless handheld mic (1.9 GHz)	
WB-LINK	Wireless belt pack transmitter (1.9 GHz)	
HBM-LINK	Headband mic (3.5mm plug)	
CM-LINK	Collar mic (3.5mm plug)	
EM-LINK	UltraLite mic (3.5mm plug)	
LM-LINK	Lapel mic (3.5mm plug)	
HBM-50	Wired headband mic (1/4" plug)	
MIC-50	Wired handheld mic (1/4" plug)	

Technical Specifications			
Rated Power Output	20 watts AC/DC		
Max SPL @ Rated Power	119 dB @ 1 meter		
Frequency Response	$400 \text{ Hz} - 10 \text{ kHz} \pm 3 \text{ dB}$		
Microphone Wireless Frequency	1.9 GHz DECT		
Microphone Wireless Range	300' + line of sight		
Battery	One 12V LFP rechargeable battery, 5.0 AH		
Charger (RC-2)	19V DC / universal input, (100Vac - 240Vac, 50 - 60 Hz)		
Dimensions (HWD)	14" x 8.5" x 3" (35.6 x 21.6 x 33 cm)		
Weight	13 lbs / 5.9 Kg		
Warranty	6 years		
Inputs			
Line	Hi-Z, unbalanced, 1/4" phone		
Wired Mic 1	Lo-Z, unbalanced, 1/4" phone		
Wired Mic 2	Lo-Z, unbalanced, 1/4" phone		
Outputs			
Line (post fader)	Lo-Z, 1/4" phone		
Speaker Out	4W, unswitched, 1/4" phone		
MEGA-AIR Technical Specifications			
AIR Frequency Range	902 - 928 MHz		
AIR Wireless Range	300' + line of sight		
Speaker In	1/4" phone		

